Driver

Carte TP-Link Archer T3U Plus

Compilation

```
git clone https://github.com/RinCat/RTL88x2BU-Linux-Driver
cd RTL88x2BU-Linux-Driver
make
sudo make install
```

Test

- Débrancher l'appareil
- Charger le driver

```
sudo modprobe 88x2bu
```

- Vérifier le chargement du driver

```
dmesg -T
[] RTW: rtl88x2bu v5.13.1-30-g37e60b26a.20220819_COEX20220812-18317b7b
[] RTW: rtl88x2bu BT-Coex version = COEX20220812-18317b7b
[] usbcore: registered new interface driver rtl88x2bu
[] RTW: module init ret=0
```

- Rebrancher a la clef et vérifier la prise en compte

```
dmesg -T | grep 88x2bu
[] 88x2bu: Unknown symbol del_timer (err -2)
[] 88x2bu: Unknown symbol del_timer (err -2)
[] 88x2bu: Unknown symbol del_timer (err -2)
[] RTW: rtl88x2bu v5.13.1-30-g37e60b26a.20220819_COEX20220812-18317b7b
[] RTW: rtl88x2bu BT-Coex version = COEX20220812-18317b7b
[] usbcore: registered new interface driver rtl88x2bu
[] rtl88x2bu 8-2:1.0 wlxb01921b70dca: renamed from wlan0
```

- vérifier le réseau

```
ip addr
```

Prise en compte au démarrage

- Créer le fichier /etc/modules-load.d/88x2bu.conf avec le nom du module

88x2bu

- Redémarrer

From:
https://wiki.iot-acs.fr/ - **Wiki**

Permanent link:
https://wiki.iot-acs.fr/doku.php?id=all:bibles:linux:ubuntu:driver

Last update: **2025/02/28 15:39**